

Bluetooth Adapter for 2 way radios



Adapter type Bluetooth dongle for connecting Bluetooth headset with 2 way radios.

Type: Bluetooth Adapter
 Operating Temp.: $-20^{\circ}\text{C}\pm 2^{\circ}\text{C} \sim 50^{\circ}\text{C}\pm 2^{\circ}\text{C}$
 Approx. Weight: 30g

BTD-XXX

Fully Qualified Bluetooth v2.0+EDR Chip set
 Chip Audio Line Input : 350mV rms (max.)
 Audio Output : 20 mV rms
 Transmitted Power : 1 dBm (typ.)
 Receiver Sensitivity : -82 dBm (typ.)
 One Key Definition
 PTT function built-in
 Power class 2,10 meters
 Display : One Color LED
 Support HSP, HFP.
 DC Input : 5 ~ 10 Vdc (std.)
 DC Current : Standby 3mA, Transmit 16 mA



RECEIVER CONNECTORS AVAILABLE

| | | |
|----------|------------|---------------|
| MOTOROLA | HT-1000 | BTD-1M3 |
| MOTOROLA | GP-328 | BTD-1M4 |
| MOTOROLA | TURBO | BTD-Turbo |
| KENWOOD | Simple-Pin | BTD-2K1,BTD-3 |
| KENWOOD | Multi-Pins | BTD-2K2 |
| ICOM | Multi-Pins | BTD-2S5 |
| VERTEX | Multi-Pins | BTD-2Y5 |
| MOTOROLA | MTP850S | BTD-850 |