

Ear Muff for 2 way radios



Muff type Speaker Microphone for connecting with 2 way radios.

Type: Ear Muff
Operating Temp.: -20°C ~ 50°C
Approx. Weight: 390g

MP-90(Black) MP-91(Carbon)

Speaker: $\Phi 40$, 300 Ω

Mic: Dynamic Type

Impedance: 150 Ω \pm 15%
Intelligent degree: -68 \pm 3dB At 1000 Hz
Rated Power Input: 0.03W
Max Power Input: 0.05W
Euzzes & Eattles: 0.387V (50Hz-2KHz)
Distortion: Less than 7%
Flux Density: \pm 10% Guass (Surface)

Connector:5 pins Mini Microphone Jack

CONNECTORS AVAILABLE

MOTOROLA	Multi-Pin / Simple-Pin
KENWOOD	Multi-Pin / Simple-Pin
ICOM	Multi-Pin / Simple-Pin
VERTEX	Multi-Pin / Simple-Pin
Others	Open End Cable